

MSH-RV SERIES | INVERTER/CHARGER

12V, 3000W

Introduction

Designed specifically for use in RVs, the MSH-RV Series inverter/charger from Sensata Technologies is a pure sine wave inverter designed with true hybrid technology allowing it to run larger loads from smaller generators.

Hybrid technology: Most inverters only use one source of energy to power loads, either from incoming AC power – shore or AC generator – or from the batteries. The MSH-RV Series combines the energy from both sources to power loads. This allows the inverter to recharge the batteries when there is surplus power or deliver more power to the loads if they require more than the AC input can supply by itself.

Built-in RV-C connector: The built in RV-C connector and protocol allows the MSH-RV Series to multiplex directly with the RV’s network bus/backbone. Program your inverter/charger settings using the RV’s system monitoring display.



Features

- Battery Profile Presets – Using ME-RC or ME-ARC Remote Controls, or built-in RV-C compliant interfaces via the ME-RVC Bridge, easily choose and set most standard battery profile settings, including Lithium Iron Phosphate (LFP) – only available via the ME-RC and ME-RVC, Gel, Flooded, AGM1, and AGM2.
- Smart Line Sense – The MSH-RV configures inputs so both outputs always receive power, whether a single input or both are connected to an AC source.
- Load Support – Load support parallels the inverter output with incoming AC sources allowing it to run larger loads from smaller generators.
- Pure Sine Wave – Power sensitive electronics without worry. The MSH-M Series provides reliable utility-grade power.
- Pass Through Capabilities – Larger 50 amp AC capability
- Multiple Ports – The MSH-RV Series provides multiple ports, including either an RV-C connector port or an RS-485 communication port for network expansion, an accessory port, and a port for a battery temperature sensor (ME-BTS).
- Convenient Wiring Access – An extra-large AC access cover with terminal screw block and 360° DC connection terminals with covers make wiring easier.
- Power Factor Corrected Charging – More efficient and works better with generators.
- Buy with Ease – The MSH-RV Series is backed by a three-year (36-month) limited warranty.

Model Numbers

- MSH3012RV-L

Available For

- RV Systems

Available Accessories

- Auto Generator Start - ME-AGS-N
- Battery Monitor Kit - ME-BMK
- Advanced Remote Control - ME-ARC50
- Remote Control - ME-RC50-L
- Smart Battery Combiner - ME-SBC



Pure Sine Wave



12

Battery Voltage Options



3000
VA

Continuous Output Options



SPECIFICATIONS

MSH3012RV-L	
INVERTER SPECIFICATIONS	
Input battery voltage operating range	9 to 17 VDC
Input battery voltage range for full output power	10.4 to 17.0 VDC
AC output voltage accuracy (at 12.6 VDC)	120 VAC $\pm 3\%$ (\leq continuous power)
Output frequency and accuracy	60 Hz ± 0.05 Hz
Total Harmonic Distortion (THD)	< 5%
Continuous power output (at 25°C)	3000 VA
Continuous AC output current (invert mode)	25 A
Continuous AC output current (charger mode)	50 A (pass-through and load support)
1 msec surge current (amps AC)	85
100 msec surge current (amps AC)	45
5 sec surge power (real watts)	3500
30 sec surge power (real watts)	3500
5 min surge power (real watts)	3400
30 min surge power (real watts)	3100
Maximum continuous input current	400 ADC
Inverter efficiency (peak)	88%
HBCO/HBCI (High Battery Cut Out/In)	17.1 VDC /16.5 VDC
LBCO/LBCI (Low Battery Cut Out/In)	13.0 VDC (adj with remote, firmware 1.9 or higher needed) / 12.5 VDC
Inverter stacking (series or parallel)	No
AC relay transfer time (minimum)	<16 msec
Power consumption – searching	10 watts
Power consumption – inverting (no load)	36 watts
Output waveform	Pure Sine Wave
CHARGER SPECIFICATIONS	
Continuous output at 25° C	125 ADC
Input current for continuous rated output	18 AAC
Maximum current during load support	224 ADC from battery
Charger efficiency	86%
AC input frequency range	50 to 70 Hz
AC input voltage range	60 to 140 VAC (120 VAC nominal)
Power factor	> 0.95

GENERAL FEATURES AND CAPABILITIES	
Transfer relay capability	50 AAC maximum each input (2 inputs)
Five stage charging capability	Bulk, Absorb, Float, Equalize (requires remote), and Battery Saver™
Battery temperature compensation	Standard with available temp sensor connected (battery temp 0 – 50 °C)
Internal cooling	0 to 120 cfm variable speed drive using dual 92mm brushless DC fans
Internal protection	Over-current protection and multipoint over-temperature protection
RVIA “RV-C” (CAN) compliant	Yes, with electrically isolated CAN port - supports up to 2 inverters per network
Corrosion protection	PCB’s conformal coated, powder coated chassis/top, and stainless steel fasteners
Safety listings	ETL listed to UL/cUL 458, CSA C22.2 No. 107.1-01
Warranty	Three years parts and labor
Branch-rated output circuit breakers	No
ENVIRONMENTAL SPECIFICATIONS	
Temperature (Operating/Non-operating)	-4° F to 140° F (-20° C to +60° C) / -40° F to 158° F (-40° C to +70° C)
Operating humidity	0 to 95% RH non-condensing
PHYSICAL SPECIFICATIONS	
Dimensions (l x w x h)	13.75” x 12.65” x 8.0” (34.9 cm x 32.1 cm x 20.3 cm)
Shipping dimensions (l x w x h)	19” x 17” x 13” (48.3 cm x 43.2 cm x 33 cm)
Mounting	Shelf or wall (vents not allowed to face downward unless ME-CB or MPX-CB is installed)
Weight	Unit: 55 lb (24.9 kg) / Shipping: 63 lb (28.6 kg)
Max operating altitude	15,000 ft (4570 m)



GENERAL NOTES

Testing for specifications at 25° C.
Specifications subject to change without notice.



AGENCY APPROVALS & CERTIFICATIONS

ETL listed to UL/cUL 458, CSA C22.2 No. 107.1-01

Sensata Technologies, Inc. (“Sensata”) data sheets are solely intended to assist designers (“Buyers”) who are developing systems that incorporate Sensata products (also referred to herein as “components”). Buyer understands and agrees that Buyer remains responsible for using its independent analysis, evaluation and judgment in designing Buyer’s systems and products. Sensata data sheets have been created using standard laboratory conditions and engineering practices. Sensata has not conducted any testing other than that specifically described in the published documentation for a particular data sheet. Sensata may make corrections, enhancements, improvements and other changes to its data sheets or components without notice.

Buyers are authorized to use Sensata data sheets with the Sensata component(s) identified in each particular data sheet. HOWEVER, NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER SENSATA INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY THIRD PARTY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT, IS GRANTED HEREIN. SENSATA DATA SHEETS ARE PROVIDED “AS IS”. SENSATA MAKES NO WARRANTIES OR REPRESENTATIONS WITH REGARD TO THE DATA SHEETS OR USE OF THE DATA SHEETS, EXPRESS, IMPLIED OR STATUTORY, INCLUDING ACCURACY OR COMPLETENESS. SENSATA DISCLAIMS ANY WARRANTY OF TITLE AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, QUIET ENJOYMENT, QUIET POSSESSION, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS WITH REGARD TO SENSATA DATA SHEETS OR USE THEREOF.

All products are sold subject to Sensata’s terms and conditions of sale supplied at www.sensata.com SENSATA ASSUMES NO LIABILITY FOR APPLICATIONS ASSISTANCE OR THE DESIGN OF BUYERS’ PRODUCTS. BUYER ACKNOWLEDGES AND AGREES THAT IT IS SOLELY RESPONSIBLE FOR COMPLIANCE WITH ALL LEGAL, REGULATORY AND SAFETY-RELATED REQUIREMENTS CONCERNING ITS PRODUCTS, AND ANY USE OF SENSATA COMPONENTS IN ITS APPLICATIONS, NOTWITHSTANDING ANY APPLICATIONS-RELATED INFORMATION OR SUPPORT THAT MAY BE PROVIDED BY SENSATA.

Mailing Address: Sensata Technologies, Inc., 529 Pleasant Street, Attleboro, MA 02703, USA.

CONTACT US

651-653-7000
800-553-6418
InverterInfo@sensata.com

Power Conversion
www.magnum-dimensions.com