

**Inverter  
Remote Control**  
Pure Sine Wave

Model  
NTX-RC



### Design Features

- Mountable remote control panel included with NTX Series 1000, 1500, 2000 and 3000 Watt inverters
- Informative LCD display indicates:
  - Battery voltage
  - Output power (bar graph)
  - Input fault
  - Output fault
- Use the control panel for remote operation and convenient status monitoring.
- Comes with 10' cable.

### 2 YEAR LIMITED WARRANTY

MODEL NO.	NTX-RC
APPLICABLE MODELS OF INVERTERS	NTX-1000-12 NTX-1500-12 NTX-2000-12 NTX-3000-12
RECEPTACLE FOR CONNECTING CABLE	8P8C (8 Position, 8 Conductor) Modular Receptacle (RJ-45)
CONNECTING CABLE TYPE	8 Conductor, Cat 5 Networking Cable
CONNECTING CABLE TERMINALS	8P8C (8 Position, 8 Conductor) Modular Plug (RJ-45)
TYPE OF CONNECTION	Straight
CONNECTING CABLE, LENGTH	3 meters / 10'
DIMENSIONS (WITHOUT CABLE), MM (L x W x H)	102 x 82 x 35
DIMENSIONS (WITHOUT CABLE), IN (L x W x H)	4.0 x 3.2 x 1.4
WEIGHT (WITHOUT CABLE), KG	0.056
WEIGHT (WITHOUT CABLE), LB	0.12

NOTE: Specifications are subject to change without notice